



Ratchet Crimp Tool complete with die set for terminating COAX 75 ohm BNC, Micro BNC and DIN 1.0/2.3 connectors to Canford group Q broadcast cables as well as Belden 1505F. Die set has the following cavities:

- 0.95mm (0.037") A/F Square for centre contact
- 1.72mm (0.068") A/F Hexagon for centre contact
- 5.41mm (0.213") A/F Hex
- 6.48mm (0.255") A/F Hex

Jaws can be reversed for left handed use.

Note that this tool may not be suitable for other brands of 75 ohm BNC, Micro BNC and DIN 1.0/2.3. Check die cavities required for your chosen connector.

Suitable Connectors:

BNC-12G 48-5062 COAX CONNS 10-005-W126-FB BNC 12G UHD Male cable, black, group Q
48-5072 COAX CONNS 10-005-W126-FB BNC 12G UHD Male cable, black, group Q (pack of 100)

BNC-3G 48-5041 COAX CONNS 10-005-B36-FA BNC 3G HD Male cable, group X
48-5051 COAX CONNS 10-005-B36-FA BNC 3G HD Male cable, group X (pack of 100)
48-5042 COAX CONNS 10-005-B36-FB BNC 3G HD Male cable, group Q
48-5052 COAX CONNS 10-005-B36-FB BNC 3G HD Male cable, group Q (pack of 100)
48-5058 COAX CONNS 10-005-B36-FE BNC 3G HD Male cable, Belden 1505F (pack of 100)

MICRO BNC-12G 48-5024 COAX CONNS 67-005-B66-FB MICRO BNC 12G UHD Male cable, group Q
48-5034 COAX CONNS 67-005-B66-FB MICRO BNC 12G UHD Male cable, group Q (pack of 100)
48-5038 COAX CONNS 67-005-B66-FE MICRO BNC 12G UHD Male cable, Belden 1505F (pack of 100)

DIN 1.0/2.3-3G 48-5004 COAX CONNS 52-005-B6-FB DIN 1.0/2.3 3G HD Male cable, group Q
48-5014 COAX CONNS 52-005-B6-FB DIN 1.0/2.3 3G HD Male cable, group Q (pack of 100)