

Crimp Tools - Cables to Connectors Cross- Reference

■ BNC, F, RCA, etc.

Model	BNC						Jack	F	RCA	Others	Suitable Die Set (*1)	Crimp Height
	BCP-B	BCP-A	BCP-C	MBCP-C	BCP-LC	BCP-H		FP-C	RCAP-C			
L-1.5C2VS/V*-1.5C			BCP-C1				BCJ-FC1 (-7/16) BCJ-RUC1				TCD-1DB	-
1.5C-2V												
L-2.5C2V		BCP-A25									TCD-35CA	1.40 - 1.47
L-2.5CFB		BCP-A25F		MBCP-C25F					RCAP-C25F			
1855A	BCP-B26											
1855P												
L-2.5CHD/L-2.5CHLT								FP-C25HD	RCAP-C25HD			
VDM230												
1855ENH												
HD PRO 0.6/2.8 AF	BCP-B28											
1506A		BCP-A32										
L-3C2V/L-3C2VS		BCP-A3				BCP-H3B BCP-H5/1	FP-C3	RCAP-C3A	MCM-V5C3 MCF-V5C3	TCD-35CA		
V3-3C/V4-3C		BCP-A3 BCP-VA3		MBCP-LC3F								MCM-V5C3 MCF-V5C3
V5-3C												
L-3CFB	BCP-B3F	BCP-A3F		MBCP-C3F	MBCP-LC3F	BCP-H3B BCP-H5/1	FP-C3F	RCAP-C3F				
V*-3CFB												
1695A		BCP-A55					FP-C55A					
VSD2001TS												
L-3C2W		BCP-A31					FP-C31			TCD-31C		
L-3CFW						BCP-H31F						
V*-3CFW	BCP-B31F											
LV-61S		BCP-A4		MBCP-C4		BCJ-C4	FP-C4	RCAP-C4A	VWP-C4A MVP-C4	TCD-4CA or TCD-451CA		
RG-59B/U												
L-4CFB/V*-4CFB				MBCP-C4F			FP-C4F	RCAP-C4F				
1505A, 1505ANH	BCP-B4F	BCP-A4F										
HD PRO 0.8/3.7 AF												
VPM2000												
L-4CHD												
1505F		BCP-A42						RCAP-C42		TCD-31C		
L-4.5CHD	BCP-B53			MBCP-C53			FP-C53A	RCAP-C53				
1694A												
HD PRO 1.0/4.8 AF	BCP-B56											
L-4.5CHWS	BCP-B45HW					BCP-H45HW				TCD-35CA		
L-5C2V/L-5C2VS		BCP-A5										
V*-5C		BCP-A5 BCP-VA5		BCP-LC5		BCP-H5B BCP-H5/1	FP-C5	RCAP-C5A				
LV-77S		BCP-A77						RCAP-C77				
L-5CFB	BCP-B5F	BCP-A5F (*2)		MBCP-C5F	BCP-LC5F	BCP-H5B BCP-H5/1 BCP-H51F	FP-C5F	RCAP-C5F		TCD-5CF or TCD-55FA excluding BCP-A5F (*2)		
V*-5CFB												
L-5CFW	BCP-B51F					BCP-H51F						
V*-5CFW												
8281F		BCP-A77						RCAP-C77				
L-5C2W		BCP-A52					FP-C52			TCD-451CA		
L-5CHD				BCP-C5HD						TCD-5HD		
L_6CHD				BCP-C6HD						TCD-67HD		
L-7CHD				BCP-C7HD								
L-7CFB				BCP-C7FA			FP-C7FA					
7731A										TCD-7CA		
9292				BCP-C71A			FP-C71A					
L-8CHD									NCP-H8HD	-		
GS-6								RCAP-C3G5		TCD-35D		

*1: Die set is not required for BCP-H series and NCP-H8HD *2: Suitable die set for BCP-A5F is TCD-35CA.

Belden: 1505A, 1505ANH, 1505F, 1506A, 1694A, 1695A, 1855A, 1855ENH, 1855P, 7731A, 8281F, 9292.

Draka: HD PRO 0.6/2.8 AF, HD PRO 0.8/3.7 AF, HD PRO 1.0/4.8 AF.

Gepeco: VDM230, VPM2000, VSD2001, VSD2001TS.

■ DIN 1.0/2.3

Model	DIN	4K-DIN	Suitable Die Set	Crimp Height
	DCP-C	MD		
L-2.5CHD/L-2.5CHLT	DCP-C25HD		TCD-D253F	1.08 - 1.16
1855A				
VDM230				
V4-2.5CHW		MDM-V4C25HW MDF-V4C25HW		
L-3CFB	DCP-C3F			
L-4CFB	DCP-C4F		TCD-D534F	1.25 - 1.33
1505A				
VPM2000				
L-4.5CHD	DCP-C53			
1694A				
VSD2001				