



Female BNC 75 Ω input - male XLR chassis connector 110 Ω output.
 For matching balanced 110 ohm digital audio circuits to unbalanced 75 ohm video circuits.

Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110 Ω to 75 Ω
- Simple to use, passive units

Technical Information

Product	NADITBNC-M
Connection Type	Adapter Male XLR to Female BNC
Frequency range	0.1 - 6 MHz
Rated voltage	≤ 5 V p-p
VSWR	< 1.1
Return loss	> 26.4 dB
Insertion Loss	< 0.3 dB @ 0.1 MHz to 10 MHz

Drawing

